



TERA TR-505-S “Stock/Factory GM/FRS & GMRS”
8 GMRS, 8 GMRS RPT
FCC Part 95E Compliant Stock/Factory Programming Chart
GMRS License Required

Channel	Description	Rx Freq	Rx PL	Tx Freq	Tx PL	Mode	Power	Scan
1	GM/FRS 1 Simplex CALL	462.5625		462.5625	141.3	W	1W	
2	GM/FRS 2 Simplex SAFETY	462.5875	141.3	462.5875	141.3	W	1W	
3	GM/FRS 3 Simplex EM	462.6125	141.3	462.6125	141.3	W	1W	
4	GM/FRS 4 Simplex	462.6375	141.3	462.6375	141.3	W	1W	
5	GM/FRS 5 Simplex	462.6625	141.3	462.6625	141.3	W	1W	
6	GM/FRS 6 Simplex	462.6875	141.3	462.6875	141.3	W	1W	
7	GM/FRS 7 Simplex	462.7125	88.5	462.7125	88.5	W	4W	
8	GMRS 15 Simplex	462.5500	88.5	462.5500	88.5	W	4W	
9	GMRS 16 Simplex	462.5750		462.5750	141.3	W	4W	
10	GMRS 17 Simplex EM	462.6000		462.6000	141.3	W	4W	
11	GMRS 18 Simplex	462.6250		462.6250	141.3	W	4W	
12	GMRS 19 Simplex	462.6500		462.6500	141.3	W	4W	
13	GMRS 20 Simplex EM TRV	462.6750		462.6750	141.3	W	4W	
14	GMRS 21 Simplex	462.7000		462.7000	141.3	W	4W	
15	GMRS 22 Simplex	462.7250		462.7250	141.3	W	4W	
16								

Side Key Assignments

Mid - Short Press	Battery Level (Report Hi/Low)
Mid - Long Press	Channel Lock (On/Off)
Low - Short Press	Tx Power (Hi/Low)
Low - Long Press	Monitor (Momentarily Open Squelch)