

Better Safe Radio™

**TERA TR-505-GTRV “GMRS, GMRS Travel Repeater & NOAA WX”
 8 GMRS, 1 GMRS RPT, 7 NOAA ‘All Hazards’ NWS WX
 FCC Part 95E Compliant Custom Programming Chart
 GMRS License Required**

Channel	Description	Rx Freq	Rx PL	Tx Freq	Tx PL	Mode	Power	Scan
1	GMRS 15 Simplex	462.5500		462.5500	88.5	W	4W	√
2	GMRS 16 Simplex	462.5750		462.5750	88.5	W	4W	√
3	GMRS 17 Simplex EM	462.6000		462.6000	88.5	W	4W	√
4	GMRS 18 Simplex	462.6250		462.6250	88.5	W	4W	√
5	GMRS 19 Simplex	462.6500		462.6500	88.5	W	4W	√
6	GMRS 20 Simplex EM TRV	462.6750		462.6750	141.3	W	4W	√
7	GMRS 21 Simplex	462.7000		462.7000	88.5	W	4W	√
8	GMRS 22 Simplex	462.7250		462.7250	88.5	W	4W	√
9	GMRS 20 Repeater 675 EM TRV	462.6750		467.6750	141.3	W	4W	
10	WX 1 M39B NOAA/NWS Rx	162.5500				W		
11	WX 2 M36B NOAA/NWS Rx	162.4000				W		
12	WX 3 M97B NOAA/NWS Rx	162.4750				W		
13	WX 4 M96B NOAA/NWS Rx	162.4250				W		
14	WX 5 M37B NOAA/NWS Rx	162.4500				W		
15	WX 6 M38B NOAA/NWS Rx	162.5000				W		
16	WX 7 M98B NOAA/NWS Rx	162.5250				W		

Side Key Assignments

Mid - Short Press	Scan Mode (On/Off)
Mid - Long Press	Channel Lock (On/Off)
Low - Short Press	Tx Power (Hi/Low)
Low - Long Press	Monitor (Momentarily Open Squelch)