

Better Safe Radio™

**TERA TR-505-LBCA5M “MURS, NOAA WX & LB Scanner”
 Long Beach, California – Neighborhood Safety MURS
 FCC Part 95J Compliant Custom Programming Chart
 No License Required**

Channel	Description	Rx Freq	Rx PL	Tx Freq	Tx PL	Mode	Power	Scan
1	MURS 1 Simplex CALL	151.8200		151.8200	88.5	N	2W	
2	MURS 2 Simplex LB SAFETY	151.8800		151.8800	203.5	N	2W	PRI
3	MURS 3 Simplex EM	151.9400		151.9400	141.3	N	2W	
4	MURS 4 Simplex BLUE DOT	154.5700		154.5700	88.5	W	2W	
5	MURS 5 Simplex GREEN DOT	154.6000		154.6000	88.5	W	2W	
6	LBPD 1 South Dispatch Rx	460.1250				N		✓
7	LBPD 2 East Dispatch Rx	460.2250				N		✓
8	LBPD 3 North Dispatch Rx	460.3500				N		✓
9	LBPD 4 West Dispatch Rx	460.2000				N		✓
10	LBPD 5 TAC 1 / Car 2 Car Rx	453.1000				N		✓
11	LBPD 6 TAC 2 / Backup Rx	453.3500				N		✓
12	LBFD 1 Fire / EMS Dispatch Rx	153.9500				N		✓
13	LBFD 2 Fire TAC 1 Dispatch Rx	153.9200				N		✓
14	LBFD 3 Fire TAC 2 Dispatch Rx	151.1600				N		✓
15	WX 1 KWO37 NOAA LA Rx	162.5500				W		
16	WX 5 WWG21 NOAA OC Rx	162.4500				W		

Side Key Assignments

Mid - Short Press	Scan Mode (On/Off)
Mid - Long Press	Channel Lock (On/Off)
Low - Short Press	Battery Level (Report Hi/Mid/Low)
Low - Long Press	Monitor (Momentarily Open Squelch)